## VCR-2020 V4.07 Upgrade Supplement

## VCR-2020 UPGRADE TO V 4.07 – SUPPLEMENT

## **Set up the Card Switches**

Switch settings on the cards will have to be set as follows:

Switch Scottings on the tales will have to be set as lone was								
Card	Switch							
Position	1	2	3	4	5	6	7	
1	OFF	OFF	OFF	ON	ON	OFF	OFF	
2	OFF	OFF	ON	ON	OFF	ON	OFF	
3	OFF	ON	OFF	ON	ON	ON	OFF	
4	OFF	ON	ON	ON	OFF	OFF	ON	
5	ON	OFF	OFF	ON	ON	OFF	ON	

Note: Switch 4 on Card 1 will probably be the only change necessary when upgrading.

## Upgrade to V4.07

- 1. Power Unit OFF.
- 2. Boot from Utility diskette:
  - Insert Utility diskette in floppy drive.
  - Power ON.
  - Hit **Enter** at Date prompt and again at Time prompt.
  - At the A:> prompt type **FDISK** and hit **Enter**.
  - Remove all disk partitions. Example follows (All items that will be displayed on screen are in *italics*. Perform operations as shown in **bold**.):
    - FDISK options will appear:
    - 1. Create DOS partition.
    - 2. Set Active partition
    - 3. Delete partition
    - 4. Display partition information Enter Choice: [1]
    - Type in 3 and Enter.

# VCR-2020 V4.07 Upgrade Supplement

•	Delete DOS Partition options will appear:
	<ol> <li>Delete Primary DOS partition</li> <li>Delete Extended DOS partition</li> <li>Delete Logical DOS Drive(s)</li> <li>Delete Non-DOS partition</li> <li>Enter Choice: []</li> </ol>
•	Type in 4 and Enter. Note: If your system does not have any NON-DOS  Partitions an error message will appear. Skip this section and proceed with option 1 to delete the Primary DOS partition.
•	What Non-DOS partition? [1] Hit Enter.
•	Continue $(Y/N)$ ? [N] Type <b>Y</b> and hit <b>Enter</b> .
•	ESC to continue Hit ESC.
•	FDISK options will appear again. Enter Choice: [1]
	Type in 3 and hit <b>Enter</b> .
•	Delete DOS Partition options will appear again.  Enter Choice: []  Type in 1 and hit Enter.
•	Which primary partition do you want to delete? [1] Hit Enter.
•	Enter volume label [ ] Hit Enter.

## VCR-2020 V4.07 Upgrade Supplement

- Are you sure (Y/N)? [N] Type in **Y** and hit **Enter**.
- ESC to continue Hit **ESC**
- Hit **ESC** again to get out of FDISK options.
- The following message will appear on the screen:

System will now restart. Press any key when ready.

- 3. Remove Utility diskette from floppy drive.
- 4. Insert MAKEVCR diskette in floppy drive and press Enter.
  - The following message will appear on the screen:

No VCR system installed Hit enter to format.

- Hit Enter.
- The following message will appear on the screen:

NO ROM BASIC SYSTEM HALTED

- 5. Remove the MAKEVCR diskette from the floppy drive.
- 6. Power the unit OFF.
- 7. Insert the VCR-2020 V4.07 diskette in the floppy drive.
- 8. Power the unit ON and allow it to fully boot from the floppy.
- 9. Remove the VCR-2020 V4.07 diskette fron the floppy drive.
- 10. Power the unit OFF and then back ON.
- 11. Allow the system to fully boot from the hard drive to verify upgrade to V4.07 has been completed successfully.
- 12. The system is now up and ready for operation.